




JX	Anschluss-Belegung	
	Elektrischer Anschluss	
..	Geometrie Polbild (Steckseite)	
AMO	Firmenname	AMO
TTL	Ausgangssignal	TTL
..	Eingangssignal	..
..	Datenschnittstelle	..
..	Teilkreiszusatzspur	..
5 polig	Kundenseitige Steckerausführung	Ader
2	Versorgung 0V (Un)	weißgrün
1	Versorgung +V (Up)	braungrün
2	Außenschirm	Schirm
3	Rechteck-Signal Ua1	violett
4	Rechteck-Signal Ua2	grau
5	Rechteck-Signal Ua0 invers	weiß

JX	Pin configuration	
	Electrical connection	
..	Geometry of pole pattern (plug side)	
AMO	company name	AMO
TTL	Output signal	TTL
..	Input signal	..
..	Data interface	..
..	Additional circular scale track	..
5-pin	Customer's connection version	Wire
2	Supply 0V (Un)	white and green
1	Supply +V (Up)	brown and green
2	External shield	Shield
3	Square-wave signal Ua1	violet
4	Square-wave signal Ua2	grey
5	Square-wave signal Ua0 inverse	white

Connection layout JX 94B05 TTL AMO				Pin Layout		Change No: C145913-05	
The reproduction, distribution and utilization of this document as well as the communication of its contents to others without express authorization is prohibited.							
		Serie		Version		Revision	
AMO GmbH		D1201853		- 01		- A - 01	
		Document No				Page 1/1	