



..	Anschluss-Belegung
	Elektrischer Anschluss
	Geometrie Polbild (Steckseite)
JH	Firmenname
..	Ausgangssignal
~1Vss	Eingangssignal
E30-RB	Datenschnittstelle
..	Teilkreiszusatzspur
14 polig	Kundenseitige Steckerausführung
3b	Versorgung 0V (Un)
4b	Versorgung 0V (0V NEXT)
3a	Versorgung +V (Up)
4a	Versorgung +V (Up NEXT)
Im Messgerät	Versorgung verbunden
1a	Spannungssignal A+
2a	Spannungssignal A-
1b	Spannungssignal B+
2b	Spannungssignal B-
7a	Spannungssignal R+
7b	Spannungssignal R-
5b	Serielle Datenübertragung SD+_NEXT
6b	Serielle Datenübertragung SD-_NEXT
5a	Serielle Datenübertragung SD+
6a	Serielle Datenübertragung SD-

..	Pin configuration
	Electrical connection
	Geometry of pole pattern (plug side)
JH	company name
..	Output signal
~1Vpp	Input signal
E30-RB	Data interface
..	Additional circular scale track
14-pin	Customer's connection version
3b	Supply 0V (Un)
4b	Supply 0V (Up NEXT)
3a	Supply +V (Up)
4a	Supply +V (Up NEXT)
In the encoder	Supply connected
1a	Voltage signal A+
2a	Voltage signal A-
1b	Voltage signal B+
2b	Voltage signal B-
7a	Voltage signal R+
7b	Voltage signal R-
5b	Serial data transfer of SD+_NEXT
6b	Serial data transfer of SD-_NEXT
5a	Serial data transfer of SD+
6a	Serial data transfer of SD-

Connection layout .. 90B14 .. E30-RB ~1Vpp .. JH				Pin Layout		Change No: C122149-15	
The reproduction, distribution and utilization of this document as well as the communication of its contents to others without express authorization is prohibited. Offenders will be held liable for the payment of damages. All rights reserved in the event of the grant of a patent, utility model or design. (ISO 16016)							
HEIDENHAIN		Serie	Version	Revision	Sheet	Page	
DR. JOHANNES HEIDENHAIN GmbH		D1379987 - 00 - A - 02				1/1	
83301 Traunreut, Germany		Document No					