





VL	Anschluss-Belegung	
	Elektrischer Anschluss	
	Geometrie Polbild (Steckseite)	
..	Ausgangssignal	..
..	Eingangssignal	..
DQ01	Datenschnittstelle	DQ01
..	Teilkreiszusatzspur	..
10 polig	Kundenseitige Steckerausführung	Litzen
B	Versorgung 0V (Un)	schwarz
A	Versorgung +V (Up)	rot
Gehäuse	Außenschirm	Schirm
3	Serielle Schnittstelle TXP	grün
6	Serielle Schnittstelle TXN	gelb
1	Serielle Schnittstelle RXP	rosa
2	Serielle Schnittstelle RXN	blau
4	Freie Litzen und Pins	
5	Freie Litzen und Pins	
7	Freie Litzen und Pins	
8	Freie Litzen und Pins	

VL	Pin configuration	
	Electrical connection	
	Geometry of pole pattern (plug side)	
..	Output signal	..
..	Input signal	..
DQ01	Data interface	DQ01
..	Additional circular-scale track	..
10-pin	Customer's connection version	Litzes
B	Supply 0V (Un)	black
A	Supply +V (Up)	red
Housing	External shield	Shield
3	Serial interface TXP	green
6	Serial interface TXN	yellow
1	Serial interface RXP	pink
2	Serial interface RXN	blue
4	Free wires and pins	
5	Free wires and pins	
7	Free wires and pins	
8	Free wires and pins	

Connection layout VL 8SS06 .. DQ01		Pin Layout		Change No: R6298	
The reproduction, distribution and utilization of this document as well as the communication of its contents to others without express authorization is prohibited. Offenders will be held liable for the payment of damages. All rights reserved in the event of the grant of a patent, utility model or design.					
HEIDENHAIN DR. JOHANNES HEIDENHAIN GmbH 83301 Traunreut, Germany		Serie	Version	Revision	Sheet
		D796683	- 00	- B	- 01
		Document No			Page 1/1