






0e	Anschluss-Belegung	
	Elektrischer Anschluss	
	Geometrie Polbild (Steckseite)	
AMO	Firmenname	AMO
~1Vss	Ausgangssignal	~1Vss
..	Eingangssignal	..
..	Datenschnittstelle	..
..	Teilkreiszusatzspur	..
8 polig	Kundenseitige Steckerausführung	Ader
5	Versorgung 0V (Un)	weißgrün
8	Versorgung +V (Up)	braungrün
Gehäuse	Außenschirm	Schirm
7	Spannungssignal A+	violett
6	Spannungssignal A-	gelb
3	Spannungssignal B+	grau
4	Spannungssignal B-	rosa
2	Spannungssignal R+	blau
1	Spannungssignal R-	weiß

0e	Pin configuration	
	Electrical connection	
	Geometry of pole pattern (plug side)	
AMO	company name	AMO
~1Vpp	Output signal	~1Vpp
..	Input signal	..
..	Data interface	..
..	Additional circular scale track	..
8-pin	Customer's connection version	Wire
5	Supply 0V (Un)	white and green
8	Supply +V (Up)	brown and green
Housing	External shield	Shield
7	Voltage signal A+	violet
6	Voltage signal A-	yellow
3	Voltage signal B+	grey
4	Voltage signal B-	pink
2	Voltage signal R+	blue
1	Voltage signal R-	weiß

Connection layout 0e 1SS08 ~1Vpp AMO				Pin Layout		Change No: C056418-05	
The reproduction, distribution and utilization of this document as well as the communication of its contents to others without express authorization is prohibited.							
		Serie		Version		Revision	
		D1214728		- 00		- A - 01	
		AMO GmbH		Document No		Page 1/1	