





7D	Anschluss-Belegung	
	Elektrischer Anschluss	
	Geometrie Polbild (Steckseite)	
JH	Firmenname	JH
TTL	Ausgangssignal	TTL
..	Eingangssignal	..
..	Datenschnittstelle	..
..	Teilkreiszusatzspur	..
17 polig	Kundenseitige Steckerausführung	Ader
P+N+T	Versorgung 0V (Un)	weißgrün
C+K+J	Versorgung +V (Up)	braungrün
Gehäuse+H	Außenschirm	Schirm
A	Rechteck-Signal Ua1	braun
D	Rechteck-Signal Ua1 invers	grün
B	Rechteck-Signal Ua2	grau
E	Rechteck-Signal Ua2 invers	rosa
F	Rechteck-Signal Ua0	rot
G	Rechteck-Signal Ua0 invers	schwarz
R+S	Zusätzliche Signale Brücken zwischen Pin	
L	Zusätzliche Signale Temperatur +	rot
M	Zusätzliche Signale Temperatur -	blau

7D	Pin configuration	
	Electrical connection	
	Geometry of pole pattern (plug side)	
JH	company name	JH
TTL	Output signal	TTL
..	Input signal	..
..	Data interface	..
..	Additional circular scale track	..
17-pin	Customer's connection version	Wire
P+N+T	Supply 0V (Un)	white and green
C+K+J	Supply +V (Up)	brown and green
Housing+H	External shield	Shield
A	Square-wave signal Ua1	brown
D	Square-wave signal Ua1 inverse	green
B	Square-wave signal Ua2	grey
E	Square-wave signal Ua2 inverse	pink
F	Square-wave signal Ua0	red
G	Square-wave signal Ua0 inverse	black
R+S	Addit. signals of bridges betw. pins	
L	Additional signals temperature +	red
M	Additional signals temperature -	blue

Connection layout 7D 3MS17 TTL JH				Pin Layout		Change No: C152702-3	
The reproduction, distribution and utilization of this document as well as the communication of its contents to others without express authorization is prohibited. Offenders will be held liable for the payment of damages. All rights reserved in the event of the grant of a patent, utility model or design. (ISO 16016)							
HEIDENHAIN DR. JOHANNES HEIDENHAIN GmbH 83301 Traunreut, Germany				Serie	Version	Revision	Sheet
				D254623 - 00 - C - 01		Page 1/1	
Document No							