






C4	Anschluss-Belegung	
	Elektrischer Anschluss	
	Geometrie Polbild (Steckseite)	
AMO	Firmenname	AMO
..	Ausgangssignal	..
..	Eingangssignal	..
EnDat22	Datenschnittstelle	EnDat22
..	Teilkreiszusatzspur	..
8 polig	Kundenseitige Steckerausführung	Ader
5	Versorgung 0V (Un)	weißgrün
1	Versorgung 0V (Sensorleitung)	weiß
8	Versorgung +V (Up)	braungrün
2	Versorgung +V (Sensorleitung)	blau
Im Messgerät	Versorgung verbunden mit Sensorleitung	Im Messgerät
Gehäuse	Außenschirm	Schirm
3	Serielle Schnittstelle Daten	grau
4	Serielle Schnittstelle Daten invers	rosa
7	Serielle Schnittstelle Takt	violett
6	Serielle Schnittstelle Takt invers	gelb

C4	Pin configuration	
	Electrical connection	
	Geometry of pole pattern (plug side)	
AMO	company name	AMO
..	Output signal	..
..	Input signal	..
EnDat22	Data interface	EnDat22
..	Additional circular scale track	..
8-pin	Customer's connection version	Wire
5	Supply 0V (Un)	white and green
1	Supply 0V (sensor line)	white
8	Supply +V (Up)	brown and green
2	Supply +V (sensor line)	blue
In the encoder	Supply connected with sensor line	In the encoder
Housing	External shield	Shield
3	Serial data transfer of data	grey
4	Serial data transfer of data, inverted	pink
7	Serial data transfer of clock pulse	violet
6	Serial data transfer of clock pulse, inverted	yellow

Connection layout C4 1SS08 .. EnDat22 AMO		Pin Layout		Change No: C047918-5	
The reproduction, distribution and utilization of this document as well as the communication of its contents to others without express authorization is prohibited.					
 AMO GmbH		Serie	Version	Revision	Sheet
		D532351 - 00 - B - 24		Page	1/1
		Document No			