



NV	Anschluss-Belegung	
	Elektrischer Anschluss	
	Geometrie Polbild (Steckseite)	
JH	Firmenname	JH
..	Ausgangssignal	..
LD/LD	Eingangssignal	LD/LD
..	Datenschnittstelle	..
KOM	Teilkreiszusatzspur	KOM
15 polig	Kundenseitige Steckerausführung	Ader
14	Versorgung 0V (Un)	weißgrün
13	Versorgung +V (Up)	braungrün
1	Rechteck-Signal Ua1	grün-schwarz
2	Rechteck-Signal Ua1 invers	gelb-schwarz
3	Rechteck-Signal Ua2	blau-schwarz
4	Rechteck-Signal Ua2 invers	rot-schwarz
5	Rechteck-Signal Ua0	rot
6	Rechteck-Signal Ua0 invers	schwarz
7	Kommutierungssignal U	grün
8	Kommutierungssignal U invers	braun
9	Kommutierungssignal V	gelb
10	Kommutierungssignal V invers	violett
11	Kommutierungssignal W	grau
12	Kommutierungssignal W invers	rosa
15	Freie Adern und Pins	weiß
	Freie Adern und Pins	blau
0078	Ergänzungen	

0078= Pin 15 darf nicht belegt werden! Nur für interne Zwecke!

NV	Pin configuration	
	Electrical connection	
	Geometry of pole pattern (plug side)	
JH	company name	JH
..	Output signal	..
LD/LD	Input signal	LD/LD
..	Data interface	..
KOM	Additional circular scale track	KOM
15-pin	Customer's connection version	Wire
14	Supply 0V (Un)	white and green
13	Supply +V (Up)	brown and green
1	Square-wave signal Ua1	green and black
2	Square-wave signal Ua1 inverse	yellow and black
3	Square-wave signal Ua2	blue and black
4	Square-wave signal Ua2 inverse	red and black
5	Square-wave signal Ua0	red
6	Square-wave signal Ua0 inverse	black
7	Commutation signal U	green
8	Commutation signal U invers	brown
9	Commutation signal V	gelb
10	Commutation signal V invers	violett
11	Commutation signal W	grau
12	Commutation signal W invers	rosa
15	Free wires and pins	white
	Free wires and pins	blue
0078	Additions	

0078= Pin 15 must not be used! Only for internal purposes!

Connection layout NV 3VB15 LD/LD KOM JH				Pin Layout		Change No: C087330-06			
The reproduction, distribution and utilization of this document as well as the communication of its contents to others without express authorization is prohibited. Offenders will be held liable for the payment of damages. All rights reserved in the event of the grant of a patent, utility model or design. (ISO 16016)									
HEIDENHAIN DR. JOHANNES HEIDENHAIN GmbH 83301 Traunreut, Germany				Serie		Version	Revision	Sheet	Page 1/1
				D730584		- 00	- A	- 04	
				Document No.					